

*** NOTE**

The IR format of the MusicCAST has been changed from 8bit typed custom code(well-known as YAMAHA NEC format) to 16bit typed though it's still NEC format.
Attached is an example of the set up process using Pronto(ProntoEdit) or RAV-2000(RAVedit).
Please see instructions.

MCX-1000										
Function	Standard I/R				IR codes for Pronto(ProntoEdit) / RAV-2000(RAVedit)*					
	Custom Code				Data Code		Predefined format For TSU-6000/RAV-2000			
STANDBY/ON	8	0	3	7	2	0	9000 006d 0002 0000 0080 0037 0020 00df			
OPEN/CLOSE	8	0	3	7	2	1	9000 006d 0002 0000 0080 0037 0021 00de			
PLAY	8	0	3	7	2	2	9000 006d 0002 0000 0080 0037 0022 00dd			
PAUSE	8	0	3	7	2	3	9000 006d 0002 0000 0080 0037 0023 00dc			
STOP	8	0	3	7	2	5	9000 006d 0002 0000 0080 0037 0025 00da			
SCAN -	8	0	3	7	2	6	9000 006d 0002 0000 0080 0037 0026 00d9			
SCAN +	8	0	3	7	2	7	9000 006d 0002 0000 0080 0037 0027 00d8			
SKIP -	8	0	3	7	2	8	9000 006d 0002 0000 0080 0037 0028 00d7			
SKIP +	8	0	3	7	2	9	9000 006d 0002 0000 0080 0037 0029 00d6			
GROUP SKIP -	8	0	3	7	2	A	9000 006d 0002 0000 0080 0037 002a 00d5			

[illegible]

[illegible]

[illegible]

TIMER	8	0	3	7	5	F	9000 006d 0002 0000 0080 0037 005f 00a0	0000 006d 0024 0000 0157 00ab 0016 0015 0016 0015 0016 0015 0016 0015 0016 0015 0016 0015 0016 0015 0016 0040 0016 0040 0016 0040 0016 0040 0016 0015 0016 0040 0016 0040 0016 0015 0016 0015 0016 0040 0016 0040 0016 0040 0016 0040 0016 0040 0016 0015 0016 0040 0016 0015 0016 0015 0016 0015 0016 0015 0016 0015 0016 0015 0016 0040 0016 0015 0016 0040 0016 05e7 0157 0055 0016 0e3b
-------	---	---	---	---	---	---	---	--

<< For Pronto(TSU-1000/2000/6000) by using ProntoEdit ver 4.0.5 >>
* NOTE : The following steps are for those who have sufficient experience using ProntoEdit.

Button Properties

Action | Properties | Icons | Colors

Alias

Delay

Set IR

Bleep

Timer

Jump: <none>

Delete

OK キャンセル 適用(A)

2. Push the view IR button.

Add IR

IR Selection

Devices:

Brands:

Code set:

Functions:

- Non applicable

Label:

View IR >> Test IR Learn IR Advanced

OK Cancel

IR Selection

Devices: Non applicable

Brands: Non applicable

Code set: Non applicable

Functions:

- Non applicable

Label

Hide IR << Test IR Learn IR Advanced

OK Cancel

IR code : 9000 006d 0002 0000 0080 0037 0060 009f

IR Selection

Devices: Non applicable

Brands: Non applicable

Code set: Non applicable

Functions: Non applicable

Label

Hide IR << Test IR Learn IR Advanced

OK Cancel

IR code :

0000	006d	0024	0000	0157	00ab	0016	0015	0016	0015
0016	0015	0016	0015	0016	0015	0016	0015	0016	0015
0016	0040	0016	0040	0016	0040	0016	0040	0016	0015
0016	0040	0016	0040	0016	0015	0016	0015	0016	0015
0016	0015	0016	0015	0016	0015	0016	0015	0016	0040
0016	0040	0016	0015	0016	0040	0016	0040	0016	0040
0016	0040	0016	0040	0016	0015	0016	0015	0016	0040
0016	05e7	0157	0055	0016	0e3b				

* NOTE : The following steps are for those who have sufficient experience using RAVedit.

Button Properties

Action | Properties | Icons | Colors |

Alias [C] UDB

Delay

Set IR

Beep

Timer

Double click

Jump: <none>

Delete

OK キャンセル 適用(A)

Add IR

IR Selection

Devices: **A_Proc**

Brands: **Non Applicable**

Functions:

- 3-stereo**
- AC-3
- Acoustic Memo
- Acoustic Select
- Antenna
- Aux
- Balance Left
- Balance Right
- Bass Down
- Bass Up
- Boost
- CD

Label

UDB

View IR >> Test IR Learn IR Advanced

OK Cancel

Predefined format

Add IR

IR Selection

Devices: A. Proc

Brands: Non Applicable

Functions:

- Stereo
- AC-3
- Acoustic Memo
- Acoustic Select
- Antenna
- Aux
- Balance Left
- Balance Right
- Bass Down
- Bass Up
- Boost
- CD

Label

UDB

Hide IR << Test IR Learn IR Advanced

OK Cancel

IR code :

9000 0064 0002 0000 0080 0037 0060 009F

Raw format

Add IR

IR Selection
 Devices:
 A. Proc
 Brands:
 Non Applicable

Functions:
 Stereo
 AC-3
 Acoustic Memo
 Acoustic Select
 Antenna
 Aux
 Balance Left
 Balance Right
 Bass Down
 Bass Up
 Boost
 CD

Label
 UDB

Hide IR << Test IR Learn IR Advanced

OK Cancel

IR code :

```
0000 006d 0024 0000 0157 00ab 0016 0015 0016 0015
0016 0015 0016 0015 0016 0015 0016 0015 0016 0015
0016 0040 0016 0040 0016 0040 0016 0040 0016 0015
0016 0040 0016 0040 0016 0015 0016 0015 0016 0015
0016 0015 0016 0015 0016 0015 0016 0015 0016 0040
0016 0040 0016 0015 0016 0040 0016 0040 0016 0040
0016 0040 0016 0015 0016 0040 0016 0015 0016 0040
0016 05e7 0157 0055 0016 0e3b
```