

RX-V440,540,640,740					
Function		Extended I/R			
		Custom Code		Data Code	
MAIN POWER ON	ON	7	E	7	E
	OFF	7	E	7	F
ZONE2 POWER	ON	7	E	B	A
	OFF	7	E	B	B
ZONE2 MUTE	ON	7	E	A	0
	OFF	7	E	A	1
AUDIO MUTE	ON	7	E	A	2
	OFF	7	E	A	3
6CH INPUT	ON	7	E	A	4
	OFF	7	E	A	5
INPUT MODE	AUTO	7	E	A	6
	DTS	7	E	A	8
	ANALOG	7	E	A	A
	AAC	7	E	3	B
SP RELAY A	ON	7	E	A	B
	OFF	7	E	A	C
SP RELAY B	ON	7	E	A	D
	OFF	7	E	A	E
ONSCREEN	OFF	7	E	B	0
	SHORT	7	E	B	1
	FULL	7	E	B	2
SLEEP	OFF	7	E	B	3
	120	7	E	B	4
	90	7	E	B	5
	60	7	E	B	6
	30	7	E	B	7
EX/ES	MATRIX ON	7	E	B	8
	AUTO	7	E	7	C
	DISCRETE ON	7	E	7	D
	OFF	7	E	B	9
EFFECT	OFF (STEREO)	7	E	E	0
	ON	7	E	2	7
PROGRAMS	CONCERT HALL	7	E	E	6
	JAZZ CLUB	7	E	E	C
	ROCK CONCERT	7	E	E	D
	DISCO	7	E	F	0
	GAME	7	E	F	2
	6/8CH STEREO	7	E	F	F
	MUSIC VIDEO	7	E	F	3
	MONO MOVIE	7	E	F	7
	VARIETY SPORTS	7	E	F	8
	SPECTACRE	7	E	F	9
	SCI-FI	7	E	F	A
	ADVENTURE	7	E	F	B
	GENERAL	7	E	F	C
	NORMAL	7	E	F	D
	ENHANCED	7	E	F	E
	PLII MOVIE	7	E	6	7
	PLII MUSIC	7	E	6	8
	DTS NEO:6 CINEMA	7	E	6	9

	DTS NEO:6 MUSIC	7	E	6	A
FM/AM	FM	7	E	B	C
	AM	7	E	B	D
	AUTO TUN UP	7	E	B	E
	AUTO TUN DOWN	7	E	B	F
DUAL MONO (Set Menu)	MAIN	7	E	9	3
	SUB	7	E	9	4
	ALL	7	E	9	5
NIGHT	TOGGLE	7	A	9	5
	ON	7	E	9	B
	OFF	7	E	9	C