

DSP-A1 STANDARD I/R CODES

FUNCTION	STANDARD SET MENU I/R				STANDARD PARAMETER I/R			
	Custom Code		Data Code		Custom Code		Data Code	
TAPE	7	D	8	B	7	D	8	B
CD	7	D	8	7	7	D	8	7
TUNER	7	D	8	9	7	D	8	9
VCR 1	7	D	8	1	7	D	8	1
LD	7	D	8	3	7	D	8	3
TV/DBS	7	D	8	4	7	D	8	4
VCR 2	7	D	8	2	7	D	8	2
DVD/VCR 3	7	D	8	5	7	D	8	5
V-AUX	7	D	8	A	7	D	8	A
TAPE 2 MON. EXT DEC.	7	D	8	C	7	D	8	C
PHONO	7	D	8	8	7	D	8	8
EFFECTS	7	D	C	1	7	D	C	1
SYSTEM POWER	7	D	9	0	7	D	9	0
POWER OFF	7	D	9	1	7	D	9	1
PLAY	7	D	9	D	7	D	C	5
SKIP FORWARD	7	D	9	E	7	D	C	6
SKIP BACKWARD	7	D	9	F	7	D	C	7
PAUSE/STOP	7	D	9	C	7	D	C	4
VOLUME +	7	D	8	D	7	D	8	D
VOLUME -	7	D	8	E	7	D	8	E
MUTE	7	D	9	4	7	D	9	4
LEVEL	7	D	9	5	7	D	9	5
TEST	7	D	C	A	7	D	C	A
SLEEP	7	D	9	3	7	D	9	3
ON SCREEN	7	D	C	2	7	D	C	2
1	7	D	D	0	7	D	D	0
2	7	D	D	1	7	D	D	1
3	7	D	D	2	7	D	D	2
4	7	D	D	3	7	D	D	3
5	7	D	D	4	7	D	D	4
6	7	D	D	5	7	D	D	5
7	7	D	D	6	7	D	D	6
8	7	D	D	7	7	D	D	7
9	7	D	D	8	7	D	D	8
10	7	D	D	9	7	D	D	9
11	7	D	D	A	7	D	D	A
12	7	D	D	B	7	D	D	B

**Bold text is for Parameter adjustments only.