

REV. 1.0

Extended IR code for RX-797, 497, 397 (NEC code)						
FUNCTION		ID1 CODE*	ID2 CODE* (Default)	RX-797	RX-497	RX-397 (only ID2)
FUNCTION						
DC1 TRG CTRL	ZONE1	7E-32	YES	NO	NO	
	ZONE2	7E-33	YES	NO	No	
	ALL OR	7E-34	YES	NO	NO	
DC1 TRG ZONE2	ON	7E-71	YES	NO	NO	
	OFF	7E-72	YES	NO	NO	
DC1 TRG ZONE1	ON	7E-73	YES	NO	NO	
	OFF	7E-74	YES	NO	NO	
ZONE2 MUTE	ON	7E-A0	YES	YES	NO	
	OFF	7E-A1	YES	YES	NO	
MAIN MUTE	ON	7E-A2	YES	YES	YES	
	OFF	7E-A3	YES	YES	YES	
SP RELAY A	ON	7E-AB	YES	YES	YES	
	OFF	7E-AC	YES	YES	YES	
SP RELAY B	ON	7E-AD	YES	YES	YES	
	OFF	7E-AE	YES	YES	YES	
SLEEP	OFF	7E-B3	YES	YES	YES	
	120	7E-B4	YES	YES	YES	
	90	7E-B5	YES	YES	YES	
	60	7E-B6	YES	YES	YES	
	30	7E-B7	YES	YES	YES	
TUNER ( AM / FM )						
PRESET GROUP	A	7A-E0	7D-AC	YES	YES	YES
	B	7A-E1	7D-AD	YES	YES	YES
	C	7A-E2	7D-AE	YES	YES	YES
	D	7A-E3	7D-AF	YES	YES	YES
	E	7A-E4	7D-B0	YES	YES	YES
FM		7E-BC	7D-27	YES	YES	YES
AM		7E-BD	7D-28	YES	YES	YES
AUTO TUNING+		7E-BE	7D-2A	YES	YES	YES
AUTO TUNING-		7E-BF	7D-2B	YES	YES	YES
TUNER ( XM )						
PRESET GROUP	A	7A-BA	7D-3A	YES	YES	NO
	B	7A-BB	7D-3B	YES	YES	NO
	C	7A-BC	7D-3C	YES	YES	NO
	D	7A-BD	7D-3D	YES	YES	NO
	E	7A-BE	7D-3E	YES	YES	NO
ALL CH SERACH		7A-B5	7D-2C	YES	YES	NO
CAT SEARCH		7A-B6	7D-2D	YES	YES	NO
PRESET SEARCH		7A-B7	7D-2E	YES	YES	NO

\* Please refer to owner's manual to change ID setting.